

# **GS2 1800 “Factory” Reprogramming Instructions**

This software update requires factory reprogramming. Any activation codes must be reentered after reprogramming. Please follow the steps below:

## ***Factory Reprogramming Method***

Factory reprogramming is the method to put a default software installation on a display. It will reset all settings to the factory defaults.

### ***Important Notes***

- **DO NOT remove switched power, unswitched power, or USB stick while reprogramming.**
- **If connecting a StarFire iTC receiver, the receiver must have the most recent software update installed (3.40N). Update the StarFire iTC using a GS2 2600, Original GreenStar Display, or the StarFire iTC Desktop Configurator.**

### ***Clean USB Drive and Load Software***

1. Insert USB stick into computer's USB port
2. Open USB drive and delete all files on USB drive.
3. Click on the link for the GS2 1800 Download and save to USB drive when prompted.

Note: To verify the download was successful, check the USB drive for the following files:

- File: SystemFilePath.txt
- Folder: FlashFiles

### ***GS2 1800 Reprogramming***

1. Turn ignition off and wait for GS2 1800 display to power down. Disconnect and reconnect harness. Insert the USB stick into the GS2 1800.
2. Hold down the 'A' and 'J' keys simultaneously while turning on power to the display. Keep keys held until the Do Not Remove Power warning is displayed.  
Note: If this screen is not seen after 30 seconds, repeat steps 1 & 2.
3. **DO NOT REMOVE THE USB STICK OR DISCONNECT POWER.**
4. When reprogramming is complete, the display will automatically reboot itself.  
Note: If the Reprogramming Unsuccessful warning is displayed, repeat steps 1-3.
5. The display will boot into its new version and the GreenStar Applications icon will be displayed in the menu.
6. Remove USB stick.